

GenSet



MG 12000 I-H/AE

GEN SET S.p.a.

Via Stazione,5 - 27030 Villanova D'Ardenghi (Pavia) Italy

Tel. (+39) 0382-5091 - Fax (+39) 0382-509-244

E-mail: genset@genset.it - internet: [//www.genset.it](http://www.genset.it)

**POWER GENERATOR
OUTPUT POWER 11 KVA SINGLE-PHASE
PETROL ENGINE 3000 RPM**

Standard Features	+ Low oil level cut out device + 12 V built-in battery + 1 x 230V - 32A EEC single-phase socket + 1 x 230V - 16A EEC single-phase socket + Power output protection + Earth Leakage Circuit Breaker + Voltmeter + Hourmeter + Central lifting eye
Options available as factory options	+ Versions with different voltages + 60Hz version + Foreseen for AMF-ATS or Remote control operation
Accessories on request	+ AMF/ATS panel for auto start operation + Remote control
Noise level	+ Lwa 98 (73 dB at 7 m)
AC generator 50Hz	+ Type: synchronous + Single-phase power (stand-by): 11kVA - 230V + Single-phase power (prime): 10kVA - 230V + Power factor: $\cos \phi$ 0,8
Petrol Engine 3000 rpm	+ Type: Honda GX630 - 2 cyl. - 688 cm³ + Max power: 19,8 hp (14,6 kWm) + Starting system: electric (12Vdc) + Cooling system: air + Fuel consumption @ 75%: 5,5 l/h
Other features	+ Insulation Class: H + Ambient temperature: 40 °C (*) + Altitude: 1000 m (*) + Mechanical Protection: IP 23 + Fuel tank capacity: 29 l + Dimensions (L x W x H): 904 x 507 x 823 mm + Dry weight: 148 kg

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.

In line with our continued development, innovation and voice of costumer program, we reserve the right to change data without notice.