

GenSet



MG 3000 I-HE



GEN SET S.p.a.

Via Stazione,5 - 27030 Villanova D'Ardenghi (Pavia) Italy

Tel. (+39) 0382-5091 - Fax (+39) 0382-509-244

E-mail: genset@genset.it - internet: [//www.genset.it](http://www.genset.it)

**PORTABLE POWER GENERATOR
OUTPUT POWER 3 KVA SINGLE-PHASE
PETROL ENGINE 3000 RPM**

Standard Features	+ Low oil level cut out device + 2 x 230V single-phase Schuko sockets + 12Vdc battery charger outlet + Power output protection
Options available as factory options	+ Not available
Accessories on request	+ Not available
Noise level	+ Lwa 95 (70 dB at 7 m)
AC generator 50Hz	+ Type: synchronous + Single-phase power (max.): 3kVA - 230V + Battery charger: 120W - 12V - 10A - DC + Power factor: $\cos \phi$ 0,8
Petrol Engine 3000 rpm	+ Type: Honda GX160 - 1 cyl. - 163 cm³ + Max power: 4,2 hp (3,1 kWm) + Starting system: manual + Cooling system: air + Fuel consumption @ 75%: 1 l/h
Other features	+ Insulation Class: H + Ambient temperature: 40 °C (*) + Altitude: 1000 m (*) + Mechanical Protection: IP 23 + Fuel tank capacity: 3,1 l + Dimensions (L x W x H): 610 x 360 x 410 mm + Dry weight: 42 kg

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.

In line with our continued development, innovation and voice of costumer program, we reserve the right to change data without notice.