

GenSet



MG 5/4 I-HE



GEN SET S.p.a.

Via Stazione,5 - 27030 Villanova D'Ardenghi (Pavia) Italy

Tel. (+39) 0382-5091 - Fax (+39) 0382-509-244

E-mail: genset@genset.it - internet: [//www.genset.it](http://www.genset.it)

PORTABLE POWER GENERATOR
OUTPUT POWER 5,5 KVA THREE-PHASE AND 2 KVA SINGLE-PHASE
PETROL ENGINE 3000 RPM

Standard Features	+ Low oil level cut out device + 1 x 400V - 16A EEC three-phase socket + 1 x 230V - 16A EEC single-phase socket + Power output protection + Earth Leakage Circuit Breaker
Options available as factory options	+ Versions with different voltages + 60Hz version
Accessories on request	+ Trolley: two-wheels and handles
Noise level	+ Lwa 95 (70 dB at 7 m)
AC generator 50Hz	+ Type: synchronous + Three-phase power (max.): 5,5kVA - 400V + Single-phase power (max.): 2kVA - 230V + Power factor: cos ϕ 0,8
Petrol Engine 3000 rpm	+ Type: Honda GX270 - 1 cyl. - 270 cm³ + Max power: 8,2 hp (6 kWm) + Starting system: manual + Cooling system: air + Fuel consumption @ 75%: 2,2 l/h
Other features	+ Insulation Class: H + Ambient temperature: 40 °C (*) + Altitude: 1000 m (*) + Mechanical Protection: IP 23 + Fuel tank capacity: 5,3 l + Dimensions (L x W x H): 720 x 480 x 515 mm + Dry weight: 80 kg

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.

In line with our continued development, innovation and voice of costumer program, we reserve the right to change data without notice.