

GenSet



MG 6000 BS/H

GEN SET S.p.a.

Via Stazione,5 - 27030 Villanova D'Ardenghi (Pavia) Italy

Tel. (+39) 0382-5091 - Fax (+39) 0382-509-244

E-mail: genset@genset.it - internet: [//www.genset.it](http://www.genset.it)

**SUPER SILENCED POWER GENERATOR
OUTPUT POWER 4,5 KVA SINGLE-PHASE
PETROL ENGINE 3000 RPM**

Standard Features	+ Low oil level cut out device + 12 V built-in battery + 1 x 230V - 16A EEC single-phase socket + Power output protection + Earth Leakage Circuit Breaker + Voltmeter + Hourmeter + Fixed wheels and concealable handles for moving
Options available as factory options	+ Versions with different voltages + 60Hz version + Foreseen for AMF-ATS or Remote control operation
Accessories on request	+ AMF/ATS panel for auto start operation + Remote control
Noise level	+ Lwa 89 (64 dB at 7 m)
AC generator 50Hz	+ Type: synchronous + Single-phase power (stand-by): 4,5kVA - 230V + Single-phase power (prime): 4kVA - 230V + Power factor: $\cos \phi$ 0,8
Petrol Engine 3000 rpm	+ Type: Honda GX270 - 1 cyl. - 270 cm³ + Max power: 8,2 hp (6 kWm) + Starting system: electric (12Vdc) + Cooling system: air + Fuel consumption @ 75%: 2,2 l/h
Other features	+ Insulation Class: H + Ambient temperature: 40 °C (*) + Altitude: 1000 m (*) + Mechanical Protection: IP 23 + Fuel tank capacity: 10,5 l + Dimensions (L x W x H): 941 x 614 x 720 mm + Dry weight: 125 kg

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.

In line with our continued development, innovation and voice of costumer program, we reserve the right to change data without notice.